Handset Overview



Quick Start Guide - Grandstream GXP2135

Phone View

The main screen will display the extension name, number and the current time.



Call View

If your phone has one or more calls active, they will be displayed on the screen.



To move between active calls, press the line key that is associated with the call. If there are multiple calls, pressing a line key will automatically place the previous call on hold.

Incoming Call Display

•412►	now/ *	04:10 PM
1157	_1 John Smith	Park 2
1167	660 📞	Park 3
	57 - Heather-GXP 2170 🚢	Parks
1167	1 RINGING	Park 4
Park 1	💼	Agent
	STATUS	Agein
=	Answer Reject	••

Placing Calls

To place a call, either:

- Pick up the handset, enter the phone number, and press the Send button or Dial soft key
- Press the speaker button, enter the phone number, and press the Send button or Dial soft key
- Activate the headset by pressing the Headset <a>O
 toggle button to on, press the call control button on the headset, enter the phone number, and press the Send
 button or Dial soft key
- 4. Press an available line key, enter the phone number, and press the **Send D** button or **Dial** soft key

Redial

- Take the phone off-hook, press the Send button, scroll to the number you wish to dial, and press the Dial soft key
- 2. To redial the last number called, press the .. (more) soft key followed by the Redial soft key

Answering Calls

To answer a call, either pick up the handset receiver, press the **Speakerphone •** button, press the **Headset •** button, or press the **Answer** soft key.

Ending Calls

To end a call, hang up the handset, press the **Speaker** button, press the call control button on the headset, or press the **End Call** soft key.

To end a call that was placed on hold, press the line key for the caller that is on hold, followed by the **End Call** soft key.

Contact Directory

To view your Directory, press the **Contacts** button, or press the **Menu** button, scroll to **Contacts**, press the **Menu** button again, and select **Local Phonebook**.

To add a contact, press the **Menu** button, scroll to the **Contacts**, press the **Menu** button again, and select **Local Phonebook**. Press the **New** soft key. Enter the contact information and press **Save**.

To delete a contact, press the **Menu** button, scroll to the **Contacts**, and press the **Menu** button again. Select **Local Phonebook**, and scroll to the contact that you would like to delete. Press the **Delete** soft key followed by **YES** to confirm the deletion.

Muting the Microphone

During a call, press the **Mute** button so that the other party cannot hear you. To disable Mute, press the **Mute** button again.

Adjusting Volume

To change the call volume, press the **Volume** -----+ button while on a call.



Quick Start Guide - Grandstream GXP2135

Blind Transfer

During an active call, press the **Transfer Press** button or the Transfer soft key and enter the extension number of the person you want to transfer the call to, followed by Blind-Trnf or Send

Attended Transfer

During an active call, press the Transfer 2 button and enter the extension number of the person you want to transfer the call to, then select the .. Soft key followed by AttnTrnf. If the recipient accepts the call press the Transfer soft key.

Call Park

During an active call, press a Park button, OR enter *5 and listen for the call park position. To unpark the call, press the **Park** button again **OR** enter the call park position number followed by the **Dial** soft key.

Place a Call on Hold

During an active call, press the **Hold U** button. To resume the call, press the **Hold D** button again or press the flashing line key of the call you wish to take off hold.

Do Not Disturb Press the Mute/Do Not Disturb 💽 button.

Page all Phones Only

Dial 77007, press Send **C**.

Page Overhead Only

Dial 77009, press Send

Page all Phones and Overhead Press the Page soft key.

Page an Extension

Dial 6xxxx (xxxx=4-digit extension) or 60xxx (xxx=3-digit extension), press Send [_____

Zone Paging Dial **7800x** (x being the page zone).

Answer Ringing Extension from a Different Handset Dial **4xxx** (**xxx**=ringing extension).

Call Queue Agent Login/Logout Dial 88008, press Send

Send Call Directly to Voicemail

Press the Transfer @ button, enter 31xxx (**xxx**=extension), and press the **Transfer** (**2**-**2**) button.

Manage Voicemail from Another Handset Dial 21xxx (xxx=extension), Send

Leave Voicemail Directly at Another Handset Dial 31xxx (xxx=extension), Send .

Retrieve Voicemail

Press the **Messages (C)** button and follow the prompts.

Record Unavailable Message

Press the **Messages (C)** button, select option **0**, then option **1**, and follow the prompts.

Three-way Conference Call

During an active call, press the **Conference** Conference and dial the third party number followed by the Send button or **Dial** soft key. When the third party answers, press the **ConfCall** soft key to begin the three-way conference.

To hold the conference, press the **Hold [11]** button. To resume the conference, press the Reconf soft key.

Conference Bridge Dial 88001, press Send .

Hot Desking/Hoteling Dial 87xxx (xxx=extension), press Send .

Viewing Call Lists

Press the History soft key on the home screen to access the call history. A label at the top of the screen identifies the type of call, from All calls to Answered, Dialed, Missed, or **Transferred** calls only. Use the navigation arrow keys to scroll vertically and horizontally through the lists.

Forward All Calls

Press the .. (more) soft key followed by the ForwardAll soft key. Enter the extension or telephone number where you would like calls forwarded to and press the **Ok** soft key. To cancel call forwarding, press the .. (more) soft key, followed by the CancelFwd soft key.



Quick Start Guide - Grandstream GXP2135

Dial Codes

Enter the code (and extension where applicable) followed by the **Dial** or **Send** soft key. Except where noted, the **xxx** in all codes below represents a 3-digit extension number.

611 – NEWT Support

911 - Emergency

38000 – Manage alternate dial sequence (Alt DS)

77007 – Page all phones only

77008 – Page all phones and overhead

77009 – Page overhead only

60xxx – Page an extension

xxx - Dial an extension

5xxx – Intercom to an extension

4xxx – Answer a ringing extension from a different phone

88008 – Call queue agent login/logout

- 21xxx Manage voicemail from another phone
- 31xxx Leave voicemail at another extension
- 88001 Access to conference bridge
- 7800x Zone paging, if enabled (x=page zone)
- 89xxx Remote call queue agent login/logout

86000 – Cell phone to Polycom handset transfer. The extension must have the "Find me Follow me" feature enabled.

Star Codes

The following star codes are used during an active call. Enter the applicable code (and extension where applicable) followed by the **Dial** or **Send** soft key. Except where noted, the **xxx** in all codes below represents a 3-digit extension number.

*6xxx – Attended transfer

*7xxx – Blind transfer

*731xxx - Voicemail transfer

*5 – Park a call. To unpark the call, press the number of the position where the call is parked followed by the **Dial** soft key.

*67 xxx-xxx-xxxx – Call blocking (xxx-xxx-xxxx=phone number being blocked)

NEWT Support Resources

To reach NEWT Technical Support:

- Dial 611 from a NEWT PBX phone
- Call Toll Free 877-777-7118
- Email newtsupport@fibernetics.ca

For access to NEWT PBX documentation and FAQs, remember to sign up for Customer Portal access at **fbs.fibernetics.ca**.

